

Power Inverter Modified Sine Wave | 24 V DC - 230 V AC | 4000 W | 2x Schuko Output

General information

Power 230-V AC devices via a 24-V DC socket with this Nedis® Power Inverter. This way, you can run household appliances, such as coffee machines, in trucks, boats etc., without having to invest in dedicated 24-V equipment. Additionally, the soft-start circuitry helps to protect your devices against damage. Equipped with 2 schuko power sockets.

Features

- Power 230-V AC devices such as coffee makers, via a 24-V battery - perfect for boats and trucks
- With soft start circuitry to protect your equipment
- Equipped with 2 schuko power sockets

Specifications

Fuse:	Yes
Input type:	Screw Terminal
Number of sockets:	2
Socket type:	F (CEE 7/3)
Output waveform:	Modified Sine Wave
Works with remote control:	No
Efficiency:	90 %
Safety functions:	Low-Battery Shutdown Protection / Thermal Protection / Output Short-Circuit Protection / Overload Protection / Too High Input Voltage Protection / Reverse Battery-Polarity Protection
Width:	210 mm
Height:	159 mm
Peak power output:	8000 W
Output power:	4000 W
Length:	580 mm
Output voltage:	230 VAC
Voltage:	AC 230 V
Input voltage:	24 VDC
Weight:	9.5 kg



Sales information

Order code:	PIMS400024
Product description:	Power Inverter Modified Sine Wave 24 V DC - 230 V AC 4000 W 2x Schuko Output
Packaging:	Giftbox
Brand name:	Nedis



Quantity	LxWxH (mm)		Weight	
1	350 mm	275 mm	685 mm	13200 g

nedis

Inverter

2x protection cap

2x protection cap

Quick start guide

**Power Inverter Modified Sine Wave | 24 V DC - 230 V AC |
4000 W | 2x Schuko Output**