

## Motion Detector | 3-Wire Installation | Adjustable Time and Ambient Light Settings

### General information

This Nedis® infrared motion sensor prevents the light from burning inadvertently, which is good for the environment - not to mention for your energy bills. It also adds the convenience of not having to turn the light on manually.

The sensor has adjustable time delay and light sensitivity settings.

This model is easy to install and suitable for 2-wire (live and neutral) and 3-wire installations (live, neutral and switch wire).

### Features

- 2 and 3-wire installation
- Adjustable ambient light setting
- Adjustable time delay setting
- Suspended ceiling mount

### Specifications

Colour:	White
Appliance:	Indoor
Width:	100 mm
Input voltage:	230 VAC 50 Hz
Sensor Technology:	PIR
Sensor reach:	0.0 - 6.0 m
Twilight setting:	3 - 2000 lx
Temperature range:	-20-40 °C
Horizontal angle of coverage:	360 °
Functions:	Motion Sensor / Adjustable Light Sensitivity / Adjustable Timer
Time setting:	10 sec - 7 min
Maximum output power fluorescent lamp:	300 W
Montage:	Ceiling
Weight:	93 g
Maximum output power filament bulbs:	5 - 300 W
Maximum output power incandescence lamp:	1200 W



### Sales information

Order code:	<b>PIRPI31WT</b>
Product description:	Motion Detector   3-Wire Installation   Adjustable Time and Ambient Light Settings
Packaging:	Giftbox with eurolock
Brand name:	Nedis



Quantity	LxWxH (mm)			Weight
<b>1</b>	103 mm	93 mm	104 mm	167 g
<b>50</b>	570 mm	215 mm	580 mm	9200 g

*nedis*

---

**Motion Detector | 3-Wire Installation | Adjustable Time and Ambient Light Settings**