

## Motion Detector | Outdoor | 3-Wire Installation | Adjustable Time, Ambient Light and Sensitivity Settings

### General information

This Nedis® infrared motion sensor prevents the light from burning inadvertently, which is good for the environment - not to mention for your energy bills. Suitable for both indoor and outdoor usage, it also adds the convenience of not having to turn the light on manually.

The sensor has adjustable time delay and light sensitivity settings and is equipped with adjustable motion sensitivity. This model is easy to install and suitable for a 2-wire (live and neutral) and 3-wire installations (live, neutral and switch wire).

### Features

- 2 and 3-wire installation
- Adjustable motion sensitivity
- Adjustable ambient light setting
- Adjustable time delay setting
- IP54 - weather proof

### Specifications

Appliance:	Indoor and Outdoor
Colour:	White
IP rating:	IP54
Weight:	132 g
Input voltage:	230 VAC 50 Hz
Width:	102 mm
Sensor Technology:	PIR
Twilight setting:	3 - 2000 lx
Temperature range:	-20-40 °C
Horizontal angle of coverage:	360 °
Functions:	Motion Sensor / Adjustable Light Sensitivity / Adjustable Timer / Adjustable Detection Sensitivity
Time setting:	10 sec - 7 min
Maximum output power fluorescent lamp:	300 W
Montage:	Ceiling
Sensor reach:	2.0 - 8.0 m
Height:	102 mm



### Sales information

Order code:	<b>PIRPO32WT</b>
Product description:	Motion Detector   Outdoor   3-Wire Installation   Adjustable Time, Ambient Light and Sensitivity Settings
Packaging:	Giftbox with eurolock
Brand name:	Nedis



Quantity	LxWxH (mm)		Weight	
<b>1</b>	114 mm	94 mm	113 mm	202 g
<b>50</b>	575 mm	205 mm	580 mm	11310 g

# nedis

---

Package contents

**Motion Detector | Outdoor | 3-Wire Installation | Adjustable  
Infrared motion sensor  
Quick start guide** **Time, Ambient Light and Sensitivity Settings**