

CATV Amplifier | Gain: 12 dB | 85-1218 MHz | Number of outputs: 2 | Return path | Silver

General information

This CATV amplifier with gain control and slope control offers one output to provide ultra-clear TV signals, with a gain of 9 dB, when connected to your television set up.

It creates an active return path which supports interactive TV and a cable (internet) modem.

Features

- Ultra-clear TV reception - and more reliable TV quality
- Gain control - allows you to match the amplifier input to the source output
- Return path - supports interactive TV and a cable (internet) modem
- Slope control - to compensate loss of signal.
- Plug and play - the F connector makes installation simple

Specifications

Material:	Metal
Colour:	Silver
Impedance:	75 Ohm
Input current:	1.0 A
Power source type:	Mains Powered
Power plug:	Type C (CEE 7/16)
Number of outputs:	2
Power adapter cable length:	1.80 m
CATV accessory type:	CATV Amplifier
Number of inputs:	1
Connector type:	F
Gain:	12 dB
Return path:	Yes
Return frequency range:	5-65 MHz
Max return path:	-6 dB
Height:	59.0 mm
Frequency range:	85-1218 MHz
Depth:	22.5 mm
Width:	94.0 mm
Noise figure:	5.5 dB
Output level:	108 dBuV



Sales information

Order code:	SAMP41120ME
Product description:	CATV Amplifier Gain: 12 dB 85-1218 MHz Number of outputs: 2 Return path Silver
Packaging:	Giftbox
Brand name:	Nedis



Quantity	LxWxH (mm)			Weight
1	105 mm	50 mm	180 mm	260 g
10	255 mm	120 mm	305 mm	2820 g
40	330 mm	265 mm	520 mm	11740 g

nedis

Amplifier
Power adapter
Installation material