

## Power Inverter Modified Sine Wave | 12 V DC - 230 V AC | 150 W | 1x Schuko / 1x USB Output

### General information

Power 230-V AC devices via a 12-V DC socket with this Nedis® Power Inverter. This way, you can run electric appliances, such as notebooks, in trucks, boats etc., without having to invest in dedicated 12-V equipment. Additionally, the soft-start circuitry helps to protect your devices against damage. Equipped with 1 schuko power socket and 1 USB port.

### Features

- Power 230-V AC devices such as notebooks, via a 12-V battery - perfect for boats and trucks
- With soft start circuitry to protect your equipment
- Equipped with 1 schuko power socket and 1 USB port

### Specifications

Weight:	0.43 kg
Fuse:	Yes
Output power:	150 W
Number of sockets:	2
Socket type:	F (CEE 7/3) / USB
Output waveform:	Modified Sine Wave
Works with remote control:	No
Efficiency:	90 %
Safety functions:	Low-Battery Shutdown Protection / Thermal Protection / Output Short-Circuit Protection / Overload Protection / Too High Input Voltage Protection / Reverse Battery-Polarity Protection
Input type:	Cigarette Lighter Plug
Height:	69 mm
Width:	94 mm
Peak power output:	300 W
Length:	165 mm
Output voltage:	230 VAC
Input voltage:	12 VDC
Voltage:	AC 230 V



### Sales information

Order code:	<b>PIMS15012</b>
Product description:	Power Inverter Modified Sine Wave   12 V DC - 230 V AC   150 W   1x Schuko / 1x USB Output
Packaging:	Giftbox
Brand name:	Nedis



Quantity	LxWxH (mm)			Weight
<b>1</b>	130 mm	85 mm	190 mm	743 g
<b>16</b>	290 mm	365 mm	395 mm	12640 g

nedis

---

Inverter

**Power Inverter Modified Sine Wave | 12 V DC - 230 V AC |**

Quick start guide

**150 W | 1x Schuko / 1x USB Output**