

# Datasheet | World Receiver Radio

**Portable Design | AM / FM / SW | Battery Powered / Mains Powered | Digital | 1.5 W | Headphone output | Alarm clock | Sleep timer | Grey**

Brand: Nedis | Article number: RDWR1000GY | Product EAN number: 5412810292196

## Product specifications

Alarm clock	<b>Yes</b>
AM frequency range	<b>522-1620 kHz</b>
AM preset stations	<b>20 pcs</b>
Antenna type	<b>External</b>
Battery play time	<b>38 hrs</b>
Colour	<b>Grey</b>
Device power input connection(s)	<b>DC Plug</b>
FM frequency range	<b>87.5 - 108 MHz</b>
Fm preset stations	<b>20</b>
Headphone output	<b>Yes</b>
Input voltage	<b>3 V DC</b>
Material	<b>ABS</b>
Media playback	<b>AUX</b>
	<b>Radio</b>
Mid-range size	<b>2 "</b>
Number of products in package	<b>1 pcs</b>
Power source type	<b>Battery Powered</b>
	<b>Mains Powered</b>
Radio design	<b>Portable Design</b>
Radio type	<b>World Receiver Radio</b>
Required batteries (not included)	<b>2x AA/LR6</b>
Screen	<b>Black Blue Screen</b>
Screen size	<b>1.3 "</b>
Sleep timer	<b>Yes</b>
Sound output	<b>Mono</b>
Speaker channels	<b>1.0</b>
Speaker peak power	<b>1.5 W</b>
Speaker RMS	<b>0.5 W</b>
Supported radio band	<b>AM</b>
	<b>FM</b>
	<b>SW</b>
SW frequency range	<b>3.70-22.05 MHz</b>
SW preset stations	<b>20</b>
Tuning type	<b>Digital</b>

## Packaging information

Brand	<b>Nedis</b>
Order code	<b>RDWR1000GY</b>
EAN single product:	<b>5412810292196</b>
EAN Inner carton:	
EAN Outer carton:	<b>5412810384464</b>
Packaging	<b>Giftbox</b>
Package contents	<b>World receiver</b>
	<b>Quick start guide</b>

Quantity	L x	W x	H (mm)	Weight
1	95 mm	40 mm	125 mm	165 g
100	265 mm	475 mm	410 mm	17200 g

