

# Datasheet | World Receiver Radio

**Portable Design | AM / FM / SW | Battery Powered / Mains Powered | Digital | 1.5 W | Headphone output | Alarm clock | Sleep timer | Grey**

Brand: Nedis | Article number: RDWR1000GY | Product EAN number: 5412810292196

## Product specifications

Alarm clock	Yes
AM frequency range	522-1620 kHz
AM preset stations	20 pcs
Antenna type	External
Battery play time	38 hrs
Colour	Grey
Device power input connection(s)	DC Plug
FM frequency range	87.5 - 108 MHz
Fm preset stations	20
Headphone output	Yes
Input voltage	3 V DC
Material	ABS
Media playback	AUX
	Radio
Mid-range size	2 "
Number of products in package	1 pcs
Power source type	Battery Powered
	Mains Powered
Radio design	Portable Design
Radio type	World Receiver Radio
Required batteries (not included)	2x AA/LR6
Screen	Black Blue Screen
Screen size	1.3 "
Sleep timer	Yes
Sound output	Mono
Speaker channels	1.0
Speaker peak power	1.5 W
Speaker RMS	0.5 W
Supported radio band	AM
	FM
	SW
SW frequency range	3.70-22.05 MHz
SW preset stations	20
Tuning type	Digital

## Packaging information

Brand	Nedis
Order code	RDWR1000GY
EAN single product:	5412810292196
EAN Inner carton:	
EAN Outer carton:	5412810384464
Packaging	Giftbox
Package contents	World receiver
	Quick start guide

Quantity	L x	W x	H (mm)	Weight
1	95 mm	40 mm	125 mm	171 g
100	265 mm	475 mm	410 mm	18020 g

