

CD Player Boombox | Battery Powered / Mains Powered | Stereo | 9 W | Bluetooth® | FM | USB playback | Carrying handle | Black

Product specifications SPBB100BK:

| Antenna type | External | | Metal | |
|----------------------------------|-----------------|--------------------------------|----------------------|--|
| Battery play time | 4 hrs | Maximum transmit antenna gain | 3.3 dBi | |
| Bluetooth [®] version | 3.0 | Maximum transmit power | 1.47 dBm | |
| Carrying handle | Yes | Media playback | AUX | |
| CD player | Yes | | CD | |
| Colour | Black | | Radio | |
| Connection input | 1x 3.5 mm | | USB | |
| | 1x USB | Number of products in package | 1 pcs | |
| Device power input connection(s) | DC 5.5 x 2.1 mm | Power adapter cable length | 1.80 m | |
| Driver size | 76 mm | Power consumption in operating | 6 W | |
| FM frequency range | 87.5 - 108 MHz | mode | | |
| Fm preset stations | 20 | Power consumption in standby | 0.2 W | |
| Frequency response | 60 Hz - 20 kHz | mode | | |
| Input current | 1.3 A | Power plug | Type C (CEE 7/16) | |
| Input voltage | 100 - 240 V AC | | - | |
| | 50/60 Hz | Power source type | Battery Powered | |
| Material | ABS | | Mains Powered | |



Datasheet | CD Player Boombox | SPBB100BK



Packaging information:

| Brand | Nedis |
|--------------------|---------------|
| Order code | SPBB100BK |
| EAN single Product | 5412810292929 |
| EAN Inner Carton | |
| EAN Outer Carton | 5412810384846 |
| Packaging | Giftbox |
| Package contents | Boombox |
| | Power adapter |
| Read more online | |

| Quantity | Lx | W x | H (mm) | Weight |
|----------|--------|--------|--------|--------|
| 1 | 250 mm | 165 mm | 235 mm | 1417 g |
| 4 | 270 mm | 355 mm | 480 mm | 6120 g |



| Required batteries (not included) | 4x C/LR14 |
|-----------------------------------|--------------------|
| Screen | Amber Screen |
| Screen size | 1.8 " |
| Sound output | Stereo |
| Speaker channels | 2.0 |
| Speaker peak power | 9 W |
| Speaker RMS | 3 W |
| Supported Bluetooth® profiles | A2DP |
| | AVDTP |
| | AVRCP |
| | HFP |
| Supported radio band | FM |
| Supported wireless technology | Bluetooth® |
| Transmit frequency range | 2402 - 2480 MHz |
| Tuning type | Digital |
| USB charging | Yes |
| | |

