



Power Inverter Modified Sine Wave | Input voltage: 12 V DC | Device power output connection(s): Type F (CEE 7/3) / USB-A | 230 V AC 50 Hz | 100 W | Peak power output: 200 W



Product specifications PIMS10012:

Colour	Silver
Device power output connection(s)	Type F (CEE 7/3)
	USB-A
Efficiency	90 %
Fuse	Yes
Input type	Cigarette Lighter Plug
Input voltage	12 V DC
Material	Aluminium
Maximum power consumption	200 W
Number of products in package	1 pcs
Number of sockets	1 pcs
Output power	100 W
Output voltage	230 V AC 50 Hz
Output waveform	Modified Sine Wave

Peak power output	200 W
Power plug	Cigarette Lighter Plug
Power source type	Car Powered
Safety functions	Low-Battery Shutdown Protection
	Output Short-Circuit Protection
	Overload Protection
	Reverse Battery-Polarity Protection
	Thermal Protection

	Too High Input Voltage Protection
Socket type	F (CEE 7/3)
	USB
Total number of USB ports	1
Works with remote control	No

Packaging information:

Brand	Nedis
Order code	PIMS10012
EAN single Product	5412810300518
EAN Inner Carton	
EAN Outer Carton	5412810373918
Packaging	Giftbox
Package contents	Inverter
	Quick start guide

Quantity	L x	W x	H (mm)	Weight
1	100 mm	85 mm	190 mm	560 g
24	310 mm	370 mm	395 mm	14360 g

