

Power Inverter Pure Sine Wave | Input voltage: 12 V DC | Device power output connection(s): Type F (CEE 7/3) | 230 V AC 50 Hz | 1000 W | Peak power output: 2000 W | Screw Terminal



Product specifications PIPS100012:

Colour	Blue	Safety functions	Low-Battery Shutdown Protection
Device power output connection(s)	Type F (CEE 7/3)		Output Short-Circuit Protection
Efficiency	85 %		Overload Protection
Fuse	Yes		Thermal Protection
Input type	Screw Terminal		Too High Input Voltage Protection
Input voltage	12 V DC		Too Low Input Voltage Protection
Material	Aluminium		F (CEE 7/3)
Maximum power consumption	2000 W		Works with remote control
Number of outputs	1		
Number of products in package	1 pcs		
Output power	1000 W		
Output voltage	230 V AC 50 Hz		
Output waveform	Pure Sine Wave		
Peak power output	2000 W		
Power plug	Screw Terminal		
Power source type	Car Powered		

Packaging information:

Brand	Nedis
Order code	PIPS100012
EAN single Product	5412810300631
EAN Inner Carton	
EAN Outer Carton	5412810374090
Packaging	Giftbox
Package contents	Inverter
	Quick start guide

Quantity	L x	W x	H (mm)	Weight
1	310 mm	145 mm	465 mm	4380 g
4	495 mm	315 mm	640 mm	18880 g

