

Power Inverter Pure Sine Wave | Input voltage: 24 V DC | Device power output connection(s): Type F (CEE 7/3) | 230 V AC 50 Hz | 1000 W | Peak power output: 2000 W | Screw Terminal



Product specifications PIPS100024:

Colour	Blue	Safety functions	Low-Battery Shutdown Protection
Device power output connection(s)	Type F (CEE 7/3)		
Efficiency	85 %		Output Short-Circuit Protection
Fuse	Yes		
Input type	Screw Terminal		Overload Protection
Input voltage	24 V DC		
Material	Aluminium		Thermal Protection
Maximum power consumption	2000 W		
Number of products in package	1 pcs		Too High Input Voltage Protection
Output power	1000 W		
Output voltage	230 V AC 50 Hz		Too Low Input Voltage Protection
Output waveform	Pure Sine Wave		
Peak power output	2000 W	Socket type	F (CEE 7/3)
Power plug	Screw Terminal		
Power source type	Car Powered	Works with remote control	Yes

Packaging information:

Brand	Nedis
Order code	PIPS100024
EAN single Product	5412810300648
EAN Inner Carton	
EAN Outer Carton	
Packaging	
Package contents	Inverter Quick start guide

Quantity	L x	W x	H (mm)	Weight
1	310 mm	140 mm	460 mm	4300 g
4	500 mm	320 mm	645 mm	18630 g

