



Power Inverter Modified Sine Wave | Input voltage: 12 V DC | Device power output connection(s): Type E (CEE 7/5) | 230 V AC 50 Hz | 100 W | Peak power output: 200 W | Cigarette Lighter Plug



Product specifications PIMS10012E:

Colour	Silver	Power source type	Car Powered	Works with remote control	No
Device power output connection(s)	Type E (CEE 7/5)		Low-Battery		
Efficiency	90 %	Safety functions	Shutdown		
Fuse	Yes		Protection		
Input type	Cigarette Lighter Plug		Output Short-Circuit		
Input voltage	12 V DC		Protection		
Material	Aluminium		Overload		
Maximum power consumption	200 W		Protection		
Number of products in package	1 pcs		Reverse Battery-Polarity		
Output power	100 W		Protection		
Output voltage	230 V AC 50 Hz		Thermal		
Output waveform	Modified Sine Wave		Protection		
Peak power output	200 W		Too High Input Voltage		
Power plug	Cigarette Lighter Plug	Total number of USB ports	1		

Packaging information:

Brand	Nedis
Order code	PIMS10012E
EAN single Product	5412810301867
EAN Inner Carton	
EAN Outer Carton	
Packaging	Giftbox
Package contents	Inverter
	Quick start guide

Quantity	L x	W x	H (mm)	Weight
1	95 mm	185 mm	85 mm	592 g
24	310 mm	370 mm	395 mm	14980 g

