



Datasheet | Power Inverter

Input voltage: 12 V DC | Device power output connection(s): Type E (CEE 7/5) | 230 V AC 50 Hz | 1000 W | Peak power output: 2400 W | Battery Clamps | Silver

Brand: Nedis | Article number: PIMS1000W12E | Product EAN number: 5412810301935

Product specifications

Colour	Silver
Device power output connection(s)	Type E (CEE 7/5)
Efficiency	90 %
Fuse	Yes
Input type	Battery Clamps
Input voltage	12 V DC
Material	Aluminium
Maximum power consumption	2400 W
Number of products in package	1 pcs
Number of sockets	2 pcs
Output power	1000 W
Output voltage	230 V AC 50 Hz
Output waveform	Modified Sine Wave
Peak power output	2400 W
Power plug	Battery Clamps
Power source type	Car Powered
Safety functions	Low-Battery Shutdown Protection
	Output Short-Circuit Protection
	Overload Protection
	Reverse Battery-Polarity Protection
	Thermal Protection
	Too High Input Voltage Protection
Works with remote control	Yes

Packaging information

Brand	Nedis
Order code	PIMS1000W12E
EAN single product:	5412810301935
EAN Inner carton:	
EAN Outer carton:	5412810373901
Packaging	Giftbox
Package contents	Inverter
	Quick start guide

Quantity	L x	W x	H (mm)	Weight
1	290 mm	140 mm	385 mm	4300 g
2	310 mm	310 mm	410 mm	9320 g

