

Quad Monoblock 4.3° | Output connection: 4x F-Connector | Noise figure range: 0.85 dB | Conversion gain: 52 - 67 dB | White | Suitable for: Astra1+ / Astra3

Brand: Nedis | Article number: SLNBQDM43BK | Product EAN number: 5412810320820

Product specifications

Colour	White
Conversion gain	52 - 67 dB
Cross polarization	20 dB
Current consumption	0.20 A
Gain flatness 26 MHz bandwidth	± 1,0 dB
High band switching	22 kHz
Image rejection (min.)	40 dB
Input frequency range high band	11.7 - 12.75 GHz
Input frequency range low band	10.7 - 11.7 GHz
LNB type	Quad Monoblock 4.3°
Local oscillator frequency phase noise	-80 dB c/Hz @ 10 kHz (max.)
Low band switching	0 kHz
Material	ABS
	Metal
Noise figure range	0.85 dB
Number of products in package	1 pcs
Operating temperature range	-35 - 70 °C
Output connection	4x F-Connector
Output frequency range high band	1.100 - 2.150 GHz
Output spurious	-53 dB
Polarity switching voltage horizontal	DC 16.0 - 20.0 V
Polarity switching voltage vertical	DC 11.0 - 14.0 V
Satellite accessory type	LNB
Suitable for	Astra1+
	Astra3

Packaging information

Brand	Nedis
Order code	SLNBQDM43BK
EAN single product:	5412810320820
EAN Inner carton:	
EAN Outer carton:	
Packaging	Giftbox
Package contents	Monoblock

Quantity	L x	W x	H (mm)	Weight
1	108 mm	105 mm	123 mm	348 g
30	395 mm	240 mm	555 mm	11400 g

