


LNB | Quad Monoblock 6.0° | Output connection: 4x F-Connector | Noise figure range: 0.85 dB | Conversion gain: 52 - 67 dB | Black | Suitable for: Astra+ / Hotbird



Product specifications SLNBQDM60BK:

Colour	Black	Noise figure range	0.85 dB
Conversion gain	52 - 67 dB	Number of products in package	1 pcs
Cross polarization	20 dB	Operating temperature range	-35 - 70 °C
Current consumption	0.20 A	Output connection	4x F-Connector
Gain flatness 26 MHz bandwidth	± 1,0 dB	Output frequency range high band	1.100 - 2.150 GHz
High band switching	22 kHz	Output spurious	-53 dB
Image rejection (min.)	40 dB	Polarity switching voltage horizontal	DC 16.0 - 20.0 V
Input frequency range high band	11.7 - 12.75 GHz	Polarity switching voltage vertical	DC 11.0 - 14.0 V
Input frequency range low band	10.7 - 11.7 GHz	Satellite accessory type	LNB
LNB type	Quad Monoblock 6.0°	Suitable for	Astra+
Local oscillator frequency phase noise	-80 dB c/Hz @ 10 kHz (max.)		Hotbird
Low band switching	0 kHz		
Material	ABS		
	Metal		

Packaging information:

Brand	Nedis
Order code	SLNBQDM60BK
EAN single Product	5412810320837
EAN Inner Carton	
EAN Outer Carton	
Packaging	Giftbox
Package contents	Monoblock

Quantity	L x	W x	H (mm)	Weight
1	108 mm	110 mm	125 mm	345 g
30	400 mm	245 mm	560 mm	11220 g

