

LNB | Twin Monoblock 4.3° | Output connection: 2x F-Connector | Noise figure range: 0.85 dB | Conversion gain: 52 - 66 dB | Black | Suitable for: Astra1+ / Astra3



Product specifications SLNBTM43BK:

Colour	Black	Noise figure range	0.85 dB
Conversion gain	52 - 66 dB	Number of products in package	1 pcs
Cross polarization	20 dB	Operating temperature range	-35 - 70 °C
Current consumption	0.17 A	Output connection	2x F-Connector
Gain flatness 26 MHz bandwidth	± 1,0 dB	Output frequency range high band	1100 - 2150 GHz
High band switching	22 kHz	Output spurious	-53 dB
Image rejection (min.)	40 dB	Polarity switching voltage horizontal	DC 16.0 - 20.0 V
Input frequency range high band	10.7 - 11.7 GHz	Polarity switching voltage vertical	DC 11.0 - 14.0 V
Input frequency range low band	11.7 - 12.75 GHz	Satellite accessory type	LNB
LNB type	Twin Monoblock 4.3°	Suitable for	Astra1+ Astra3
Local oscillator frequency phase noise	-80 dB c/Hz @ 10 kHz (max.)		
Low band switching	0 kHz		
Material	ABS Metal		

Packaging information:

Brand	Nedis
Order code	SLNBTM43BK
EAN single Product	5412810320875
EAN Inner Carton	
EAN Outer Carton	
Packaging	Giftbox
Package contents	Monoblock

Quantity	L x	W x	H (mm)	Weight
1	109 mm	110 mm	127 mm	337 g
30	395 mm	240 mm	550 mm	10900 g

