

**Twin Monoblock 6.0° | Output connection: 2x F-Connector | Noise figure range: 0.85 dB | Conversion gain: 52 - 67 dB | Black | Suitable for: Astra+ / Hotbird**

Brand: Nedis | Article number: SLNBTM60BK | Product EAN number: 5412810320882

**Product specifications**

Colour	<b>Black</b>
Conversion gain	<b>52 - 67 dB</b>
Cross polarization	<b>20 dB</b>
Current consumption	<b>0.17 A</b>
Gain flatness 26 MHz bandwidth	<b>± 0,5 dB</b>
High band switching	<b>22 kHz</b>
Image rejection (min.)	<b>40 dB</b>
Input frequency range high band	<b>11.7 - 12.75 GHz</b>
Input frequency range low band	<b>10.7 - 11.7 GHz</b>
LNB type	<b>Twin Monoblock 6.0°</b>
Local oscillator frequency phase noise	<b>-80 dB c/Hz @ 10 kHz (max.)</b>
Low band switching	<b>0 kHz</b>
Material	<b>ABS</b> <b>Metal</b>
Noise figure range	<b>0.85 dB</b>
Number of products in package	<b>1 pcs</b>
Operating temperature range	<b>-35 - 70 °C</b>
Output connection	<b>2x F-Connector</b>
Output frequency range high band	<b>1100 - 2150 GHz</b>
Output spurious	<b>-53 dB</b>
Polarity switching voltage horizontal	<b>DC 16.0 - 20.0 V</b>
Polarity switching voltage vertical	<b>DC 11.0 - 14.0 V</b>
Satellite accessory type	<b>LNB</b>
Suitable for	<b>Astra+</b> <b>Hotbird</b>

**Packaging information**

Brand	<b>Nedis</b>
Order code	<b>SLNBTM60BK</b>
EAN single product:	<b>5412810320882</b>
EAN Inner carton:	
EAN Outer carton:	
Packaging	<b>Giftbox</b>
Package contents	<b>Monoblock</b>

Quantity	L x	W x	H (mm)	Weight
1	108 mm	110 mm	125 mm	338 g
30	400 mm	240 mm	560 mm	11020 g

