

FM Radio | Jobsite Radio | FM | Battery Powered / Mains Powered | Digital | 15 W | Screen size: 2.2 " | Blue White Screen | IPX5 | Carrying handle | Black / Yellow



Product specifications RDFM3100YW:

Antenna type	External
Battery play time	22 hrs
Bluetooth® version	4.2
Carrying handle	Yes
Colour	Black
	Yellow
Connection input	1x 3.5 mm
Device power input connection(s)	DC Power Connector
FM frequency range	87.5 - 108 MHz
Fm preset stations	20
Input current	1.0 A
Input voltage	9 V DC
IP rating	IPX5
Material	ABS
	Rubber
Maximum transmit antenna gain	0 dBi
Maximum transmit power	-6 dBm

Media playback	AUX
	Radio
Mid-range size	2.4 "
Number of products in package	1 pcs
Power adapter cable length	1.50 m
Power cable side A	C7
Power cable side B	DC Power adapter
Power consumption in operating mode	8 W
Power consumption in standby mode	0 W
Power plug	Type C (CEE 7/16)
Power source type	Battery Powered
	Mains Powered
Radio design	Jobsite Radio

Radio type	FM Radio
Required batteries (not included)	6x C/LR14
Screen	Blue White Screen
Screen size	2.2 "
Shock protection	Yes
Sound output	Mono
Speaker channels	1.0
Speaker peak power	15 W
Speaker RMS	5 W
Supported Bluetooth® profiles	A2DP
	AVRCP
Supported radio band	FM
Transmit frequency range	2402 - 2480 MHz
Tuning type	Digital

Packaging information:

Brand	Nedis
Order code	RDFM3100YW
EAN single Product	5412810326266
EAN Inner Carton	
EAN Outer Carton	5412810384358
Packaging	Giftbox
Package contents	Jobsite radio
	Power cable

Read more online

Quantity	L x	W x	H (mm)	Weight
1	200 mm	330 mm	205 mm	2530 g
4	420 mm	355 mm	420 mm	10860 g

