

Wireless Doorbell Set | Battery Powered | 3 V DC | 1x CR2032 | Volume: 80 dB | Signal range: 300 m | IP44 | 36 Melodies | 1 Receiver | White



Product specifications DOORB212WT:

| | | | |
|-------------------------------|-------------------|-----------------------------------|-------------------|
| Accessories | Double-sided Tape | Number of products in package | 1 pcs |
| | Quick Start Guide | Number of receivers | 1 Receiver |
| | Receiver | Power plug | Type C (CEE 7/16) |
| | Transmitter | Power source type | Battery Powered |
| Colour | White | Required batteries (included) | 1x CR2032 |
| Doorbell features | 36 Melodies | Required batteries (not included) | 2x AA/LR6 |
| | Easy Installation | Signal range | 300 m |
| | Pre-set Code | Supported wireless technology | 433 MHz |
| Input current | 0.2 A | Transmit frequency range | 0 - 433 MHz |
| Input voltage | 3 V DC | Volume | 80 dB |
| IP rating | IP44 | | |
| Material | ABS | | |
| Maximum transmit antenna gain | 0 dBi | | |
| Maximum transmit power | 10 dBm | | |
| Number of melodies | 36 Melodies | | |

Packaging information:

| | |
|--------------------|-------------------------|
| Brand | Nedis |
| Order code | DOORB212WT |
| EAN single Product | 5412810327973 |
| EAN Inner Carton | 5412810394517 |
| EAN Outer Carton | 5412810378296 |
| Packaging | Blister |
| Package contents | Receiver Transmitter |

Read more online

| Quantity | L x | W x | H (mm) | Weight |
|----------|--------|--------|--------|--------|
| 1 | 85 mm | 140 mm | 125 mm | 178 g |
| 6 | 255 mm | 120 mm | 255 mm | 1200 g |
| 36 | 380 mm | 280 mm | 530 mm | 7700 g |

