



Datasheet | Wireless Doorbell Set

Battery Powered | 3 V DC | 1x CR2032 | Volume: 80 dB | Signal range: 300 m | IP44 | 36 Melodies | 1 Receiver | Black

Brand: Nedis | Article number: DOORB212BK | Product EAN number: 5412810328055

Product specifications

| | |
|-----------------------------------|--------------------------|
| Accessories | Double-sided Tape |
| | Quick Start Guide |
| | Receiver |
| | Transmitter |
| Colour | Black |
| Doorbell features | 36 Melodies |
| | Easy Installation |
| | Pre-set Code |
| Input current | 0.2 A |
| Input voltage | 3 V DC |
| IP rating | IP44 |
| Material | ABS |
| Maximum transmit antenna gain | 0 dBi |
| Maximum transmit power | 10 dBm |
| Number of melodies | 36 Melodies |
| Number of products in package | 1 pcs |
| Number of receivers | 1 Receiver |
| Power plug | Type C (CEE 7/16) |
| Power source type | Battery Powered |
| Required batteries (included) | 1x CR2032 |
| Required batteries (not included) | 2x AA/LR6 |
| Signal range | 300 m |
| Supported wireless technology | 433 MHz |
| Transmit frequency range | 0 - 433 MHz |
| Volume | 80 dB |

Packaging information

| | |
|---------------------|----------------------|
| Brand | Nedis |
| Order code | DOORB212BK |
| EAN single product: | 5412810328055 |
| EAN Inner carton: | 5412810394500 |
| EAN Outer carton: | 5412810378289 |
| Packaging | Blister |
| Package contents | Receiver |
| | Transmitter |

| Quantity | L x | W x | H (mm) | Weight |
|----------|--------|--------|--------|--------|
| 1 | 85 mm | 145 mm | 125 mm | 182 g |
| 6 | 260 mm | 125 mm | 255 mm | 1180 g |
| 36 | 380 mm | 280 mm | 530 mm | 7580 g |

