

# Datasheet | Car FM Transmitter

**Tiltable | Hands free calling | 1.1 " | LED Screen | Bluetooth® | PD 18 W / 5.0 V DC / 1.0 A | Fast charging | Google Assistant / Siri | Black / Grey**

Brand: Nedis | Article number: CATR130BK | Product EAN number: 5412810330720

## Product specifications

Bluetooth® version	<b>5.0</b>
Built-in microphone	<b>Yes</b>
Colour	<b>Black</b>
	<b>Grey</b>
Device power output connection(s)	<b>1x USB</b>
	<b>1x USB-C™</b>
Fast charging	<b>Yes</b>
FM frequency range	<b>87.6 - 107.9 MHz</b>
Frequency response	<b>20 Hz - 20 KHz</b>
Hands free calling	<b>Yes</b>
Input current	<b>3 A</b>
Input voltage	<b>12 - 24 V DC</b>
Material	<b>ABS</b>
Maximum transmit antenna gain	<b>-0.68 dBi</b>
Maximum transmit power	<b>4 dBm</b>
Number of products in package	<b>1 pcs</b>
Output current	<b>1.0 A</b>
Output voltage	<b>5 V DC</b>
Power plug	<b>Car Adapter</b>
Power source type	<b>Car Powered</b>
Screen	<b>LED Screen</b>
Screen size	<b>1.1 "</b>
Signal to Noise Ratio	<b>45 dB</b>
Supported audio codec	<b>FLAC</b>
	<b>MP3</b>
	<b>WAV</b>
Supported Bluetooth® profiles	<b>A2DP</b>
	<b>AVRCP</b>
	<b>HSP</b>
Supported radio band	<b>FM</b>
Supported wireless technology	<b>Bluetooth®</b>
Transmit frequency range	<b>2402 - 2480 MHz</b>
Transmitter design	<b>Tiltable</b>
USB charging	<b>5.0 V DC / 1.0 A</b>
	<b>PD 18 W</b>
Voice control support	<b>Google Assistant</b>

Voice control support

**Siri**

## Packaging information

Brand	<b>Nedis</b>
Order code	<b>CATR130BK</b>
EAN single product:	<b>5412810330720</b>
EAN Inner carton:	<b>5412810396351</b>
EAN Outer carton:	<b>5412810383399</b>
Packaging	<b>Giftbox with eurolock</b>
Package contents	<b>Bluetooth® FM transmitter</b>
	<b>Quick start guide</b>

Quantity	L x	W x	H (mm)	Weight
1	105 mm	70 mm	190 mm	130 g
6	225 mm	115 mm	395 mm	980 g
36	410 mm	380 mm	470 mm	6740 g

