

SmartLife LED Filament Bulb | Wi-Fi | E14 | 470 lm | 4.9 W | Warm White | 1800 - 3000 K | Glass | Android™ / IOS | Candle



Product specifications WIFILRF10C37:

| | | | |
|-----------------------------------|------------------|-------------------------------|------------------------|
| App available for | Android™ | Light source | LED |
| | IOS | Material | Glass |
| Base | E14 | Maximum power consumption | 4.9 W |
| Beam angle | 320 ° | Maximum transmit antenna gain | 1 dBi |
| Bulb diameter | 45 mm | Maximum transmit power | 17 dBm |
| Bulb height | 110 mm | Number of switching cycles | 15000 Switching Cycles |
| Colour | White | Operating temperature | -20 - 45 °C |
| Colour rendering index (Ra) | 80 | Rated life time of lamp | 10000 h |
| Colour temperature | 1800 - 3000 K | Rated luminous flux | 470 lm |
| Compatible with | Nedis® SmartLife | Technology | Filament LED |
| Energy class | F | | LED |
| Energy consumption per 1000 hours | 4.9 kWh | Transmit frequency range | 2412 - 2472 MHz |
| Input voltage | 220 - 240 V AC | Wattage equivalent | 40 W |
| Lamp finish | Golden | Wireless technology | Wi-Fi |
| Lamp shape | Candle | | |
| Light colour | Warm White | | |

Packaging information:

| | |
|--------------------|---|
| Brand | Nedis |
| Order code | WIFILRF10C37 |
| EAN single Product | 5412810335664 |
| EAN Inner Carton | |
| EAN Outer Carton | |
| Packaging | Giftbox with eurolock |
| Package contents | <ul style="list-style-type: none"> ▪ Smart bulb ▪ Quick start guide |

| Quantity | L x | W x | H (mm) | Weight |
|----------|--------|--------|--------|--------|
| 1 | 65 mm | 140 mm | 65 mm | 70 g |
| 10 | 75 mm | 265 mm | 330 mm | 800 g |
| 50 | 350 mm | 285 mm | 375 mm | 4380 g |

