

Zigbee 3.0 | Battery Powered / USB Powered | Detector angle: 100 ° | Detector range: 7 m | Max. battery life: 24 Months | White

Brand: Nedis | Article number: ZBSM20WT | Product EAN number: 5412810408894

Product specifications

| | |
|----------------------------------|-------------------------|
| App available for | Android™ |
| | IOS |
| Battery type | CR123A |
| Colour | White |
| Compatible with | Nedis® SmartLife |
| Control through mobile app | Yes |
| Detector angle | 100 ° |
| Detector range | 7 m |
| Device power input connection(s) | Micro USB |
| Input current | 0.02 A |
| Input voltage | 1.5 V DC |
| Material | Plastic |
| Max. battery life | 24 Months |
| Maximum power consumption | 0.05 W |
| Maximum transmit antenna gain | 1 dBi |
| Maximum transmit power | 10 dBm |
| Number of products in package | 1 pcs |
| Operating temperature range | -10 - 50 °C |
| Power plug | USB |
| Power source type | Battery Powered |
| | USB Powered |
| Required batteries (included) | 1x CR123A |
| Sensor technology | PIR |
| Supported wireless technology | Zigbee 3.0 |
| Transmit frequency range | 2405 - 2480 MHz |

Packaging information

| | |
|---------------------|------------------------------|
| Brand | Nedis |
| Order code | ZBSM20WT |
| EAN single product: | 5412810408894 |
| EAN Inner carton: | 5412810442904 |
| EAN Outer carton: | 5412810442898 |
| Packaging | Giftbox with eurolock |
| Package contents | PIR motion sensor |
| | Quick start guide |

| Quantity | L x | W x | H (mm) | Weight |
|----------|--------|--------|--------|---------|
| 1 | 45 mm | 150 mm | 65 mm | 91 g |
| 8 | 100 mm | 145 mm | 265 mm | 802 g |
| 120 | 290 mm | 465 mm | 520 mm | 12920 g |



Zigbee Motion Sensor (PIR)



App control



Schedule & timer

