

Datasheet | FM Radio

Portable Design | FM | Battery Powered / Mains Powered | Digital | 3.6 W | Screen size: 2.0 " | Black White Screen | Headphone output | Black / White

Brand: Nedis | Article number: RDFM2100WT | Product EAN number: 5412810272457

| Product specifications | | | |
|--|---|--|--|
| Antenna type | External | | |
| Battery capacity | 400 mAh | | |
| Charging time | 3 h | | |
| Colour | Black | | |
| | White | | |
| Connection input | 1x USB | | |
| | microSD | | |
| Connection output | 1x 3.5 mm | | |
| Device power input connection(s) | DC 12 x 4.5 mm | | |
| FM frequency range | 87.5 - 108 MHz | | |
| Fm preset stations | 50 | | |
| Headphone output | Yes | | |
| Input current | 1.0 A | | |
| Input voltage | 5 V DC | | |
| Material | ABS | | |
| Maximum battery play time | 3 hrs | | |
| Media playback | AUX | | |
| | Micro SD | | |
| | Radio | | |
| | USB | | |
| Power cable length | 1.00 m | | |
| Power cable side A | USB | | |
| Power cable side B | DC Power adapter | | |
| | De Fower adapter | | |
| Power plug | USB | | |
| Power plug Power source type | • | | |
| | USB | | |
| | USB Battery Powered | | |
| Power source type | USB Battery Powered Mains Powered | | |
| Power source type Radio design | USB Battery Powered Mains Powered Portable Design | | |
| Power source type Radio design Radio type | USB Battery Powered Mains Powered Portable Design FM Radio | | |
| Power source type Radio design Radio type Required batteries (included) | USB Battery Powered Mains Powered Portable Design FM Radio N/A | | |
| Power source type Radio design Radio type Required batteries (included) Screen | USB Battery Powered Mains Powered Portable Design FM Radio N/A Black White Screen | | |
| Power source type Radio design Radio type Required batteries (included) Screen Screen size | USB Battery Powered Mains Powered Portable Design FM Radio N/A Black White Screen 2.0 " | | |
| Power source type Radio design Radio type Required batteries (included) Screen Screen size SmartLife | USB Battery Powered Mains Powered Portable Design FM Radio N/A Black White Screen 2.0 " | | |
| Power source type Radio design Radio type Required batteries (included) Screen Screen size SmartLife Speaker channels | USB Battery Powered Mains Powered Portable Design FM Radio N/A Black White Screen 2.0 " No Mono | | |

| Tuning type | Digital |
|--------------|---------|
| USB charging | Yes |

| Packaging information | | | | |
|-----------------------|----------------------|--|--|--|
| Brand | Nedis | | | |
| Order code | RDFM2100WT | | | |
| EAN single product: | 5412810272457 | | | |
| EAN Inner carton: | | | | |
| EAN Outer carton: | | | | |
| Packaging | Giftbox | | | |
| Package contents | FM radio | | | |
| | Rechargeable battery | | | |

| Lx | Wx | H (mm) | Weight |
|--------|------------------|-------------------------------|--|
| 135 mm | 96 mm | 40 mm | 261 g |
| 255 mm | 200 mm | 145 mm | 3241 g |
| 300 mm | 410 mm | 270 mm | 13340 g |
| | 135 mm 255 mm | 135 mm 96 mm 255 mm 200 mm | Lx W x H (mm) 135 mm 96 mm 40 mm 255 mm 200 mm 145 mm 300 mm 410 mm 270 mm |





