



Power Inverter Modified Sine Wave | Input voltage: 24 V DC | Device power output connection(s): Type F (CEE 7/3) | 230 V AC 50 Hz | 600 W | Peak power output: 1500 W | Battery Clamps | Silver



Product specifications PIMS600W24:

Colour	Silver	Safety functions	Low-Battery Shutdown Protection
Device power output connection(s)	Type F (CEE 7/3)		Output Short-Circuit Protection
Efficiency	90 %		Overload Protection
Fuse	Yes		Reverse Battery-Polarity Protection
Input type	Battery Clamps		Thermal Protection
Input voltage	24 V DC		Too High Input Voltage Protection
Material	Aluminium		SmartLife
Maximum power consumption	1500 W		No
Number of products in package	1 pcs	Works with remote control	No
Number of sockets	1 pcs		
Output power	600 W		
Output voltage	230 V AC 50 Hz		
Output waveform	Modified Sine Wave		
Peak power output	1500 W		
Power plug	Battery Clamps		
Power source type	Car Powered		

Packaging information:

Brand	Nedis
Order code	PIMS600W24
EAN single Product	5412810300556
EAN Inner Carton	
EAN Outer Carton	5412810374076
Packaging	Giftbox
Package contents	Inverter
	Quick start guide

Quantity	L x	W x	H (mm)	Weight
1	245 mm	115 mm	285 mm	2300 g
6	315 mm	380 mm	510 mm	14780 g

