

Power Inverter Modified Sine Wave | Input voltage: 12 V DC | Device power output connection(s): Type F (CEE 7/3) | 230 V AC 50 Hz | 1000 W | Peak power output: 2400 W | Battery Clamps | Silver



Product specifications PIMS1000C12:

Colour	Silver	Safety functions	Low-Battery Shutdown Protection
Device power output connection(s)	Type F (CEE 7/3)		
Efficiency	90 %		Output Short-Circuit Protection
Fuse	Yes		
Input type	Battery Clamps		Overload Protection
Input voltage	12 V DC		
Material	Aluminium		Reverse Battery-Polarity Protection
Maximum power consumption	2400 W		
Number of products in package	1 pcs		Thermal Protection
Number of sockets	2 pcs		
Output power	1000 W		Too High Input Voltage Protection
Output voltage	230 V AC 50 Hz		
Output waveform	Modified Sine Wave	SmartLife	No
Peak power output	2400 W	Works with remote control	No
Power plug	Battery Clamps		
Power source type	Car Powered		

Packaging information:

Brand	Nedis
Order code	PIMS1000C12
EAN single Product	5412810300587
EAN Inner Carton	
EAN Outer Carton	5412810373871
Packaging	Giftbox
Package contents	Inverter Power Cable

Read more online

Quantity	L x	W x	H (mm)	Weight
1	295 mm	145 mm	455 mm	6220 g
2	315 mm	305 mm	475 mm	13220 g

