

Power Inverter Pure Sine Wave | Input voltage: 12 V DC | Device power output connection(s): Type F (CEE 7/3) | 230 V AC 50 Hz | 150 W | Peak power output: 300 W | Cigarette Lighter Plug



Product specifications PIPS15012:

Colour	Blue
Device power output connection(s)	Type F (CEE 7/3)
Efficiency	85 %
Fuse	Yes
Input type	Cigarette Lighter Plug
Input voltage	12 V DC
Material	Aluminium
Maximum power consumption	300 W
Number of outputs	1
Number of products in package	1 pcs
Output power	150 W
Output voltage	230 V AC 50 Hz
Output waveform	Pure Sine Wave
Peak power output	300 W
Power cable side B	Car Adapter

Power plug	Cigarette Lighter Plug
Power source type	Car Powered
Safety functions	Low-Battery Shutdown Protection
	Output Short-Circuit Protection
	Overload Protection
	Thermal Protection
	Too High Input Voltage Protection
	Too Low Input Voltage Protection

SmartLife	No
Socket type	F (CEE 7/3)
Works with remote control	No

Packaging information:

Brand	Nedis
Order code	PIPS15012
EAN single Product	5412810300624
EAN Inner Carton	
EAN Outer Carton	5412810374106
Package contents	Inverter Quick start guide

Quantity	L x	W x	H (mm)	Weight
1	180 mm	115 mm	245 mm	1487 g
10	390 mm	275 mm	570 mm	15820 g

