

Power Inverter Pure Sine Wave | Input voltage: 12 V DC | Device power output connection(s): Type F (CEE 7/3) | 230 V AC 50 Hz | 2000 W | Peak power output: 4000 W | Screw Terminal



Product specifications PIPS200012:

Colour	Blue	Safety functions	Low-Battery Shutdown Protection
Device power output connection(s)	Type F (CEE 7/3)		
Efficiency	85 %		Output Short-Circuit Protection
Fuse	Yes		
Input type	Screw Terminal		Overload Protection
Input voltage	12 V DC		
Material	Aluminium		Thermal Protection
Maximum power consumption	4000 W		
Number of outputs	2		Too High Input Voltage Protection
Number of products in package	1 pcs		
Output power	2000 W		Too Low Input Voltage Protection
Output voltage	230 V AC 50 Hz		
Output waveform	Pure Sine Wave	SmartLife	No
Peak power output	4000 W		
Power plug	Screw Terminal		
Power source type	Car Powered		Works with remote control

Packaging information:

Brand	Nedis
Order code	PIPS200012
EAN single Product	5412810300655
EAN Inner Carton	
EAN Outer Carton	5412810374113
Packaging	
Package contents	Inverter
	Quick start guide

