

Power Inverter Modified Sine Wave | Input voltage: 12 V DC | Device power output connection(s): Type E (CEE 7/5) | 230 V AC 50 Hz | 100 W | Peak power output: 200 W | Cigarette Lighter Plug



Product specifications PIMS10012E:

Colour	Silver	Power source type	Car Powered	Total number of USB ports	1
Device power output connection(s)	Type E (CEE 7/5)		Low-Battery	Works with remote control	No
Efficiency	90 %	Safety functions	Shutdown Protection		
Fuse	Yes		Output Short-Circuit Protection		
Input type	Cigarette Lighter Plug		Overload Protection		
Input voltage	12 V DC		Reverse Battery-Polarity Protection		
Material	Aluminium		Thermal Protection		
Maximum power consumption	200 W		Too High Input Voltage Protection		
Number of products in package	1 pcs				
Output power	100 W	SmartLife	No		
Output voltage	230 V AC 50 Hz				
Output waveform	Modified Sine Wave				
Peak power output	200 W				
Power plug	Cigarette Lighter Plug				

Packaging information:

Brand	Nedis
Order code	PIMS10012E
EAN single Product	5412810301867
EAN Inner Carton	
EAN Outer Carton	
Packaging	Giftbox
Package contents	Inverter
	Quick start guide

Quantity	L x	W x	H (mm)	Weight
1	95 mm	185 mm	85 mm	592 g
24	310 mm	370 mm	395 mm	14980 g

