

Single | Output connection: 1x F-Connector | Noise figure range: 0.90 dB | Conversion gain: 53 - 65 dB | White

Brand: Nedis | Article number: SLNB10SWT | Product EAN number: 5412810320806

Product specifications

Colour	White
Conversion gain	53 - 65 dB
Cross polarization	18 dB
Current consumption	0.08 A
Gain flatness 26 MHz bandwidth	± 0,5 dB
High band switching	22 kHz
Image rejection (min.)	40 dB
Input frequency range high band	11.7 - 12.75 GHz
Input frequency range low band	10.7 - 11.7 GHz
LNB type	Single
Local oscillator frequency phase noise	-80 dB c/Hz @ 10 kHz (max.)
Low band switching	0 kHz
Material	ABS
	Metal
Noise figure range	0.90 dB
Number of products in package	1 pcs
Operating temperature range	-40 - 70 °C
Output connection	1x F-Connector
Output frequency range high band	1.100 - 2.150 GHz
Output spurious	-60 dB
Polarity switching voltage horizontal	DC 16.0 - 20.0 V
Polarity switching voltage vertical	DC 11.0 - 14.0 V
Satellite accessory type	LNB
SmartLife	No

Packaging information

Brand	Nedis
Order code	SLNB10SWT
EAN single product:	5412810320806
EAN Inner carton:	
EAN Outer carton:	5412810384839
Packaging	Giftbox
Package contents	LNB

Quantity	L x	W x	H (mm)	Weight
1	65 mm	105 mm	65 mm	104 g
135	340 mm	335 mm	575 mm	14820 g

