



SmartLife Motion Sensor | Light Sensor | Zigbee 3.0 | Battery Powered / USB Powered | Detector angle: 100 ° | Detector range: 7 m | Max. battery life: 24 Months | White



Product specifications ZBSM20WT:

App available for	Android™	Operating temperature range	-10 - 50 °C
	IOS	Power plug	USB
Battery type	CR123A	Power source type	Battery Powered
Colour	White		USB Powered
Compatible with	Nedis® SmartLife	Required batteries (included)	1x CR123A
Control through mobile app	Yes	Sensor technology	PIR
Detector angle	100 °	Sensor type	Light Sensor
Detector range	7 m	SmartLife	Yes
Device power input connection(s)	Micro USB	Supported wireless technology	Zigbee 3.0
Input current	0.02 A	Transmit frequency range	2405 - 2480 MHz
Input voltage	1.5 V DC		
Material	Plastic		
Max. battery life	24 Months		
Maximum power consumption	0.05 W		
Maximum transmit antenna gain	1 dBi		
Maximum transmit power	10 dBm		
Number of products in package	1 pcs		

Packaging information:

Brand	Nedis
Order code	ZBSM20WT
EAN single Product	5412810408894
EAN Inner Carton	5412810442904
EAN Outer Carton	5412810442898
Packaging	Giftbox with eurolock
Package contents	PIR motion sensor
	Quick start guide

Quantity	L x	W x	H (mm)	Weight
1	45 mm	150 mm	65 mm	91 g
8	100 mm	145 mm	265 mm	802 g
120	290 mm	465 mm	520 mm	13400 g



Zigbee Motion Sensor (PIR)



App control



Schedule & timer

