

SmartLife Power Switch | Zigbee 3.0 | 2.5 W | Terminal Connection | App available for: Android™ / IOS



Product specifications ZBGDN10RD:

| | | | |
|-----------------------------------|------------------------------------|-------------------------------|-----------------|
| App available for | Android™ IOS | Mounting | Wall Mount |
| Colour | Red | Number of products in package | 1 pcs |
| Compatible with | Nedis® SmartLife | Operating temperature range | -10 - 40 °C |
| Device power input connection(s) | Garage Door Terminal Connection | Output current | 5 A |
| Device power output connection(s) | Terminal Connection | Output power | 2.5 W |
| Input current | 5 A | SmartLife | Yes |
| Input voltage | 100 - 240 V AC 50/60 Hz | Supported wireless technology | Zigbee 3.0 |
| IP rating | IP20 | Transmit frequency range | 2400 - 2484 MHz |
| Material | Plastic | | |
| Maximum power consumption | 2 W | | |
| Maximum transmit antenna gain | 2 dBi | | |
| Maximum transmit power | 10 dBm | | |

Packaging information:

| | |
|--------------------|-------------------------------------------------------|
| Brand | Nedis |
| Order code | ZBGDN10RD |
| EAN single Product | 5412810452194 |
| EAN Inner Carton | 5412810452286 |
| EAN Outer Carton | 5412810452293 |
| Packaging | Giftbox |
| Package contents | Smart Garage Door Opener module Installation Guide |

| Quantity | L x | W x | H (mm) | Weight |
|----------|--------|--------|--------|--------|
| 1 | 30 mm | 155 mm | 65 mm | 83 g |
| 10 | 165 mm | 70 mm | 260 mm | 911 g |
| 100 | 280 mm | 370 mm | 345 mm | 9580 g |

